



Tripp Lite
1111 West 35th Street
Chicago, IL 60609 USA
Telephone: +(773) 869 1234
E-mail: saleshelp@tripplite.com

Model #: PV2400FC

PowerVerter® Plus 2400W Industrial-Strength Inverter with 2 Outlets

Highlights



- Designed for heavy duty and motor loads
- 24V DC input; 120V AC output; 2 outlets
- 2400W continuous output
- Peak surge output: OverPower (up to 1 hour)—3600W; Double-Boost (up to 10 seconds)—4800W
- High-efficiency power conversion
- Automatic overload protection

Description

Continuously supplies up to 2400W of 120V AC power to 2 AC outlets from any 24V battery or automotive DC source. Frequency control locks AC output at 60Hz for operating stability of motor loads. Includes a set of high current DC input terminals for simple, permanent installation. Highly reliable large transformer design specializes in powering motors and other inductive loads with high-current startup needs.

Applications

- Industrial power tools, pumps, appliances, mobile office equipment, audio/video devices, and more.

Package Includes

- PV2400FC Inverter
- Instruction manual

Features

- Converts 24V DC battery power to 120V AC power
- 2400W continuous output power
- Peak surge output: OverPower (up to 1 hour), 3600 watts; Double-Boost (up to 10 seconds), 4800W
- Set of 2 bolt-down DC wiring terminals for 24V battery connection; 2 x NEMA 5-15/20R outlets
- Frequency control for operating stability
- High-efficiency operation conserves batteries to prolong run time
- Diagnostic LEDs indicate load level (high, medium, and low) and battery charge (high, medium, and low)
- DC fusing protects inverter against overload
- High-impact polycarbonate housing
- RJ45 port allows connection of APS/PowerVerter Remote Switch ([APSRM4](#))

Specifications

OUTPUT	
Frequency compatibility	60 Hz

Output watts	2400
Continuous output capacity (watts)	2400
Peak output capacity (watts)	4800
Output nominal voltage	120V
Output voltage regulation	Maintains PWM sine wave output voltage of 120 V AC (+/-5%)
Output frequency regulation	60 Hz (+/- 0.3 Hz)
Overload protection	Circuit breaker
Outlet quantity / type	2 AC outlets
INPUT	
Recommended Electrical Service	Requires 24V DC input source capable of delivering 120A for the required duration (when used at full capacity). For automotive applications, professional hardwire installation with 250A battery system fusing is recommended
Maximum input amps / watts	Full continuous load - 120A at 24V DC; No load - 2.2A at 24V DC
Input connection type	Set of 2 bolt-down DC wiring terminals
Input cord length details	User supplies cabling; 2/0 gauge or larger recommended
Voltage compatibility (VDC)	24
BATTERY	
DC system voltage (VDC)	24
LEDS ALARMS & SWITCHES	
Switches	3-position on/off/remote switch enables simple on/off power control plus "remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional APSRM4 accessory
Front panel LEDs	Set of 6 LEDs provides continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences
PHYSICAL	
Shipping weight (lbs)	43
Shipping weight (kg)	19.5
Cooling method	Fan
Unit Dimensions (HWD/in)	7.25 x 8.5 x 16.25
Unit Dimensions (HWD/cm)	18.42 x 21.59 x 41.28
Shipping Dimensions (HWD/in)	13.5 x 15 x 21.5
Shipping Dimensions (HWD/cm)	34.29 x 38.1 x 54.61
Unit weight (lbs)	39

Unit weight (kg)	17.7
Material of construction	Polycarbonate
Style	Heavy-duty
Form factors supported	Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information)
ENVIRONMENTAL	
Relative Humidity	0-95% non-condensing
SPECIAL FEATURES	
Appearance	Attractive all-black color scheme
Remote control capability	Yes
WARRANTY	
Product Warranty Period (Worldwide)	1-year limited warranty

Related Items

Optional Products

Related Model	Description	Qty.
APSRM4	Remote Control Module - for Tripp Lite Inverters and Inverter/Chargers	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/en/products/model.cfm?variables.txtModelID=182.

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.